

Fire alarm ancillaries



24V Vibrating Pillow Pad

Ref. BCT363

- Provides early warning of a potential fire alarm condition to the hard of hearing.
- Connects to a standard 24V DC conventional fire alarm sounder circuit via a separately-available BCT363 Single Gang Locking Jack Socket.
- Typically used under pillows in hotel bedrooms, etc.
- Includes a 2m connection lead (users are advised to leave a minimum amount of the connection lead on the bed to minimise the risk of entanglement).

Application/operation	Designed to connect to the BCT363 connection plate. Typically placed under a pillow to warn the hard of hearing of a fire alarm.
Supply/operating voltage	Supply/operating voltage 24V DC nominal; 27V DC max (via BCR363 plate).
Activation current	Activation current 120mA nominal; 160mA max.
Product dimensions	97mm diameter x D 34mm; Connection lead measures 2m.
Weight	150g.
Operating conditions / temperature	-10°C to +60°C.
Notes	The BCT363 pad is not designed for continuous use and should not be left running for prolonged periods without being reset. The responsible person must ensure the vibrator's location is satisfactory to wake the user when in alarm.

